

## **AXIS T8341 PIR Motion Sensor**

## Wireless motion detector

AXIS T8341 PIR Motion Sensor detects motion both day and night, thanks to passive infrared technology. By communicating wirelessly with AXIS M5065 PTZ Network Camera or connected Z-Wave Plus® controllers, the motion sensor can be used in small security solutions with less cabling. The wireless I/O connectivity also enables flexible installation as the sensor can easily be moved and adapted to your needs, even for mounting in corners.

- > Wireless I/O connectivity
- > Z-Wave Plus® compatibility
- > S2 security compliant
- > Battery included






WWW.CXIS.COM T10116879/EN/M1.7/1801

## **AXIS T8341 PIR Motion Sensor**

Supported products	AXIS M5065 PTZ Network Camera Compatible with other Z-Wave Plus® control devices
Network	
Supported protocols	Z-Wave Plus®. For more information on the supported command classes, see the product's User Manual
General	
Casing	Plastic Color: white
Sustainability	PVC free
Power	1 x CR123 3.0 V Lithium battery Battery life: 1 year
Distance	Transmitting range up to 100 meters (328 ft)
Frequency	908.42 MHz (US), 922.5 MHz (JP)
Operating conditions	-10 °C to 40 °C (14 °F to 104 °F)
Storage conditions	-20 °C to 60 °C (-4 °F to 140 °F)
Approvals	EMC FCC Part 15 Subpart B Class B, ICES-003 Class B, VCCI Class B
Dimensions	62 x 42 x 87 mm (2.44 x 1.65 x 3.43 in)
Weight	72 g (0.15 lbs)
Included accessories	Installation guide, mounting kit, 1 x CR123 3.0 V Lithium battery
Warranty	Axis 3-year warranty, see www.axis.com/warranty



www.axis.com/environmental-responsibility

